STAR HEADLIGHT & LANTERN CO.



Specifications and Features

- Trunk mount amplifier with remote control head
- · Wail, Yelp, Air Horn, Phaser, Manual, and Two-Tone
- Eight light functions
- Four position progressive slide switch with LED
- · Integrated public address microphone
- Dual color backlighting on keypad (Amber and
- Park kill input, auxiliary input
- · Positive or negative switching for auxiliary and park kill inputs
- Replaceable jumpers and dip switches for option
- Universal mounting bracket or flange mount available
- Drives one or two 100 watt speakers
- LED speaker diagnostics

- · High and low voltage shut down protection
- Self-resetting circuit protection against speaker shorts
- Ships complete with positive locking connector, mic. clip, mounting bracket, hardware, thirty standard function replacement labels. RFI filter. and instructions
- Dimensions LCS800 and LCS850: Control head with flange: 4 ¹¹/₆₄"H x 7 ¹¹/₁₆"W x 1/8"D, Control head without flange: 3 ³/₁₆"H x 6 ¹¹/₁₆"W x ¹/₈"D, Amp: 2 1/2"H x 7"W x 7 3/8"D (plus 3/4" flange on each side)
- Weight: **LCS800**, **LCS800-F** (with flange) 8.5 lbs **LCS850**, **LCS850-F** (with flange) - 9.5 lbs
- Output: 100 or 200 watts (one or two speakers)
- Input: 10-16V DC
- Siren tone frequency: 675-1633Hz
- Amp Draw: 8 amps (per speaker)
- Approvals: Exceeds Acoustical and Environmental requirements of SAE J1849, CA Title 13 (when used with SVP driver(s) and approved tones)

Model Numbers/Descriptions:

	LCS800-008	Siren with light control
	LCS800-8F	Siren with light control, with flange
	LCS850-8	Siren with light and arrow stick controller
	LCS850-8F	Siren with light and arrow stick controller, with flange

SF049 Rev C 4-22-2017





Star Headlight & Lantern Co., Inc. 455 Rochester Street Avon, NY 14414

Phone: 585-226-9500 Fax: 888-478-2797 starheadlight.com



